




PRODUCT DATASHEET

Notecarrier Datasheet

Notecarrier B v1.0

Notecarrier B is a compact 45mm x 45mm Notecarrier designed for building highly customized hardware solutions. It provides the Notecard edge connector socket, a micro-USB port for power and USB Serial access to Notecard, and u.FL connections for user-provided cellular/WiFi and GPS antennas.

Blues Notecarrier® Datasheet: Notecarrier B v1.0



Warning

While this product is still supported, it is no longer available for purchase from the Blues store. We recommend the [Notecarrier X](#) and [Notecarrier XM](#) as updated alternatives.

Functional Description

Notecarriers are available in multiple form factors to support rapid development across a range of use cases. Depending on the variant, a Notecarrier may prioritize direct host integration, compact size, integrated cellular/WiFi and GNSS antennas, or the ability to be soldered directly into a low-volume production design.

Notecarriers are explicitly designed to bridge the gap between early prototyping and a production-ready Notecard-based solution. In a final product, the Notecard is typically socketed directly onto a custom PCB via an edge connector, alongside the customer's MCU, sensors, and supporting circuitry. While this approach provides maximum flexibility and modularity, it can significantly increase the effort required during initial development and validation.

To simplify this process, Notecarriers expose the Notecard's interfaces through convenient breakout connections and integrate essential supporting circuitry, including power regulation, protection, and signal conditioning. This allows developers to focus on firmware, connectivity, and system behavior without first designing a complete custom carrier board.

Features

- **Simple.** Provides breadboard compatible pins or solderable mask for direct connections.
- **Compatible.** Level shifters ensure compatibility with 3.3V or 5V equipment.
- **Convenient.** Powered by a USB connector (requires 2A supply).
- **GPS Ready.** Models are either active GPS compatible, or feature a built-in antenna to enable GNSS connectivity.

Compatible Notecards


Due to differences in the physical size of Notecards, certain Notecarriers are only compatible with certain Notecards. The **Notecarrier B v1.0** is compatible with:

- [Notecard Cellular](#)[↗]
- [Notecard Cellular \(Legacy\)](#)[↗]
- [Notecard WiFi](#)[↗]
- [Notecard LoRa](#)[↗]

Package Configuration

Notecarrier B (Basic) v1.0

Notecarrier B (CARR-B) is designed for building highly customized hardware solutions.



- [Notecard edge connector socket](#) and [mounting screw receptacle](#).
- Micro-USB port to power Notecarrier and provide a USB Serial command interface to Notecard.
- Requires user provided U.FL cellular/WiFi antenna and optional U.FL active GPS antenna.
- PCB Dimensions: 45mm x 45mm
- Center of Mounting Holes: 36mm x 36mm (measured from the edge of the PCB to the center of the furthest mounting hole)

Power Information

All Notecarriers can be powered by connecting directly to the USB port. However, most installations will not have USB power available, so several alternate power options are provided by the various Notecarrier models:

- applying 2.5-5.5VDC to the **V+** pin.

Commonly provided via DC power supply or non-rechargeable battery.

Warning

Typical USB ports may only be capable of supplying 500 mA of current, which might not be enough to power Notecard during a cellular connection to a GSM network (which can spike to 2A). In this situation, you're advised to supplement power to your Notecarrier with an external source (e.g. a LiPo battery).

GPS (GNSS) Antenna Requirements

All Notecarrier models are designed to support active GPS, and several Notecarrier models provide built-in antennas ready to be connected to a Cellular Notecard using the included u.FL cables.

Active GPS Ready

The Notecarrier B, Notecarrier Pi, and Notecarrier R models do not have integrated GPS antennas, but support active GPS by providing circuitry to enable bias voltage to be supplied.

The Notecarrier B v1.0 has a 0Ω resistor connecting the two pins. The resistor can be removed, allowing you to either utilize a passive GPS antenna, or splice into the circuit and provide your own bias voltage.

Header Descriptions

Notecarrier B Dual 9-pin Headers

Pin Name	Direction	Usage		Usage	Direction	Pin Name
AUX1	IN/OUT	API-selectable modes of operation		UART serial receive request interface (Notecard has onboard 10K pull-up resistors)	IN	RX
AUX2	IN/OUT	API-selectable modes of operation		UART serial transmit request interface	OUT	TX
AUX3	IN/OUT	API-selectable modes of operation		I2C data request interface (Notecard has onboard 10K pull-up resistors)	IN/OUT	SDA
AUX4	IN/OUT	API-selectable modes of operation		I2C clock request interface (Notecard has onboard 10K pull-up resistors)	IN/OUT	SCL
AUXEN	IN	Enable diagnostics		Configurable interrupt signal	OUT	ATTN
AUXRX	IN	High-speed diagnostic interface		For development use only: MUST normally be NC or High Impedance and must never be pulled to GND. A VIO-level pulse of >250ms will reset the Notecard.	IN	RST

Pin Name	Direction	Usage		Usage	Direction	Pin Name
AUXTX	OUT	High-speed diagnostic interface		For On/Off switching of customer product. Leave NC or connect to a physical switch or Open Drain output. Notecard will be OFF if pulled to GND. Never apply positive voltage to this pin.	IN	EN
VUSB	IN/OUT	Direct connect to VUSB pin of the USB connector		2.5-5.5V, < 8 μ A@5V idle, < 500mA typical, 2A surge max (GPRS)	IN	V+
VIO	OUT	Digital I/O voltage source with 100mA available		Ground	IN	GND

Specifications

Electrical Characteristics

DC Characteristics

Description	Minimum	Maximum	Unit
Supply Voltage	2.5	5.5	V
Supply Current	500	2000	mA

Absolute Maximum Ratings

Description	Minimum	Maximum	Unit
Storage temperature	-35	70	°C

Note

Actual values may vary based on local conditions such as atmospheric conditions and distance to the cell tower.

Ordering Information

- [Notecarriers](#) 
- [Development Kits](#) 

Design Files

Open source hardware designs for all Notecarriers are maintained in the [note-hardware](#)  GitHub repository.

This Notecarrier's versioned folder contains the mechanical and electrical design resources for that revision, such as board drawings, dimensional PDFs, Gerber fabrication files, a BOM spreadsheet, and a STEP (`.stp` / `.step`) 3D model suitable for enclosure design and CAD integration.

Board Errata

Terms and Conditions

Visit [Blues Hardware Terms & Conditions](#)[↗].

Revision History

Author	Date	Summary
Ray Ozzie	2019-2020	Document drafted
John Wiedey	2020	Various improvements
Sean Taylor	2020	Various improvements
Zachary J. Fields	01 OCT 2020	Updated information and translated to markdown
Brandon Satrom	04 JAN 2021	Added link to design resources
Greg Wolff	13 JAN 2021	Added BAT pin information to Notecarrier AF datasheet
Brandon Satrom	07 APR 2022	Added Notecarrier A information
Zachary J. Fields	20 JUL 2022	Added Notecarrier F information
Zachary J. Fields	24 OCT 2022	Added Notecarrier B v2 information
Rob Lauer	28 OCT 2022	Added versioning for Notecarrier B v1/v2
TJ VanToll	05 JAN 2023	Added Notecard Outboard Firmware Update information
Rob Lauer	28 FEB 2023	Re-labeling Notecarrier B as "Basic"

Author	Date	Summary
Rob Lauer	01 MAR 2023	Added PCB/Mounting Hole Dimensions
Rob Lauer	07 SEP 2023	Added Notecarrier F v1.3 information
Rob Lauer	16 NOV 2023	Added Notecarrier Pi v2.0 information
Rob Lauer	14 MAR 2024	Added Notecarrier B v3.1 and Notecarrier R v1.0 information
Rob Lauer	05 JUN 2024	Added Notecarrier XS v1.1 information
Rob Lauer	10 JUN 2024	Added KiCad schematics to A, B, F, and Pi Notecarriers
Rob Lauer	18 JUL 2024	Added Notecarrier XS v1.2 information
Rob Lauer	22 JUL 2024	Updated Notecarrier pin descriptions
TJ VanToll	19 AUG 2024	Added Notecarrier X v1.2, XM 1.2, and XP 3.1 information
Rob Lauer	14 JAN 2026	Added Notecarrier CX v1.3 information
Rob Lauer	11 FEB 2026	Added Notecarrier A v2.3 information
Rob Lauer	22 MAY 2026	Added Notecarrier CX v1.7 information

Author	Date	Summary
Rob Lauer	11 JUN 2026	Added Notecarrier XI v1.4 information
Rob Lauer	16 JUL 2026	Corrected Notecarrier XI DC specifications and Starnote for Iridium antenna details
Rob Lauer	03 AUG 2026	Add newly updated KiCad schematics
Rob Lauer	19 AUG 2026	Added Notecarrier XI v1.4 board errata

Contact Information

Blues Inc.

<https://blues.com> 

50 Dunham Ridge Suite 1650

Beverly, MA 01915

support@blues.com 

Can we improve this page? [Send us feedback](#)